

SP110E Bluetooth LED controller operating instructions

1. Features:

1. App Control via Bluetooth 4.0, long Control distance, convenient to use;
2. Support almost every kind of one-wire or two-wire LED driver IC ;
3. Brightness adjustable, With 120 kinds of patterns, which are vivid and beautiful;
4. Support setting total pixel number, able to control up to 1024 pixels;
5. DC5V~12V wide working voltage, preventing reverse connection of power supply;
6. User setting saving;

2. App:

Both IOS version and Android OS version are available.

- Requires IOS version 10.0 or later;
- Requires Android OS version 4.4 or later;
- Search "LEDHue" in App Store or Google play or scan this QR code to download and install the App:



3. Specifications:

Working temperature : -20°C~60°C;

Working Voltage : DC5V~12V;

Working Current : 20mA~40mA;

Remote distance : 20 Meters;

Product size : 50mm*20mm*10mm;

Product weight : 20g ;

Certificates : CE, RoHS;

4. Wire Connection:

